

MP610U 6 Zones Paging and Music Mixer Amplifier with USB & Tuner

This mixing amplifier is rated at 250W and 4-16 Ω speaker output are provided. There are 3 unbalanced microphones inputs and 3 aux inputs. Bass and treble controls are provided. This amplifier can be applied to different occasions, such as supermarket, classroom, etc. Extensive protection from short-circuit, overload and high temp is ensured. Automatic cooling system ensures the extreme quite sound system.

Features:

- 100V & 4-16 Ω , rated power 250W
- Support USB / SD / FM radio, with built-in chime
- 4 MIC inputs, Mic 1 with priority and muting fun
- 3 AUX line input & 1 AUX line output for power extension
- Each AUX & Mic input with individual volume



Model	MP610U
Rated output	250W
Speaker output	100V & 4-16 Ω ,
Input sensitivity	MIC: 3.0mV(\pm 0.5mV) LINE: 300mV(\pm 50mV)
Frequency response	80Hz-16kHz (\pm 3dB)
Distortion	Less than 1% (at 1kHz, 1/3 rated output voltage)
The ratio of signal to noise	MIC: more than 71dB LINE: more than 85dB
Protection	DC voltage; overload; short-circuit.
Power requirements	AC 220V-240V/50Hz-60Hz
Power consumption	500W

Outer Packing Size (mm)	(L×W×H)520×430×195
Unit Size (mm)	(L×W×H)418×338×88
Gross weight	14kg
Net weight	16kg

Connection Chart

